

Model Number 1051V1	PERFORMANCE SPECIFICATION		
	DYNAMIC FORCE SENSOR, IEPE	REV B, ECN 13810, 10/20/17	



- COMPRESSIVE & TENSILE LOADINGS
- EXCELLENT LINEARITY
- IEPE, VOLTAGE MODE

		ENGLIS	H	SI		
PHYSICAL			_		_	
Weight, Max.		1.0	OZ	28	grams	
Connector		10-32		10-32		
Material		Stainless Steel		Stainless Steel		
Sensing Element	Material	Quartz		Quartz	]	
	Mode	Compression		Compression	]	
		•	•	•	='	
PERFORMANCE					_	
Sensitivity, ± 10 %		500	mV/lbf	112.4	mV/N	
Compression Range		10	lbf	44.5	N	
Maximum Compression		200	lbf	890	N	
Tension Range		10	lbf	44.5	N	
Maximum Tension [1]		200	lbf	890	N	
Resolution		0.00014	lbf, rms	0.00062	N	
Linearity [2]		±1	% Full Scale	±1	% Full Scale	
Resonant Frequency, Unloaded		75	kHz	75	kHz	
Stiffness, Force Sensor		11.4 lbf/µin		2.0	kN/μm	
			-		="	
ENVIROMENTAL			_		_	
Maximum Shock, Unloaded		10,000	g pk	98100	m/s <sup>-</sup>	
Maximum Vibration, Unloaded		5,000	g pk	49050	m/s <sup>∠</sup>	
Temperature Range		-100 to +250	°F	-73 to +121	°C	
Thermal Coefficient		0.03	%/°F	0.05	%/°C	
Seal		Ероху		Epoxy	1	
					-	
ELECTRICAL						
Output Voltage F.S		±5	V	±5	V	
Output Impedance		<100	Ω	<100	Ω	
Bias Voltage		7.5 to 11.5	VDC	7.5 to 11.5	VDC	
Compliance Voltage Range		18 to 30	VDC	18 to 30	VDC	
Supply Current Range [3]		2 to 20	mA	2 to 20	mA	
Discharge Time Constant, Nom		50	Sec	50	Sec	
			1	•	-	
1						

nis	family	also	includes:	

The falling also included							
Model	Sens. (mV/lbf)	Compression Range (lbf)	Max. Compression (lbf)	Tension Range (lbf)	Max. Tension (lbf)	T.C. (sec)	Resolution (lbf, RMS)
1051V2	100	50	1000	50	500	100	0.0007
1051V3	50	100	2000	100	500	500	0.0014
1051V4	10	500	10000	500	500	2000	0.007
1051V5	5	1,000	15000	500	500	2000	0.014
1051V6	1	5,000	15000	500	500	2000	0.07


Refer to the performance specifications of the products in this family for detailed description.


## Supplied Accessories:

- 1) Accredited calibration certificate (ISO 17025) 2) MOD 6210 STEEL IMPACT CAP
- 3) MOD 6204 1/4-28 MOUNTING STUD

## [1] Absolute maximum tension. Do not exceed in any case!

- [2] Percent of full scale or any lesser range, zero based best-fit straight line method.
- [3] Power the device only with constant current type power units. Do not apply power to this system without current limting. This will destroy the integral IC amplifier.





Units on the line drawing are in inches, units in brackets are in millimeters. Refer to 127-1051V for more information.

